
Printed: 02/11/2022


iscover




AES LiFePO₄ Solar Stationary Battery

Discover® Advanced Energy System (AES) LiFePO₄ Lithium solar batteries offer bankable performance and the lowest cost of energy storage per kWh. AES LiFePO₄ Lithium batteries are manufactured with the highest-grade ${\sf LiFePO_4}$ cells and feature a proprietary high peak surge and transient voltage hardened BMS that delivers superior peak power, lightning fast charge and discharge rates and LYNK Solar Gateway functionality for Plug-and-play closed loop integration with the worlds best known off-grid inverters and chargers turning a good system into a great one.







TERMINAL



MECHANICAL SPECIFICATIONS

0

1

(D)

◍

Length A (in/mm)	18.5	470
Width B (in/mm)	13.7	348
Height C (in/mm)	14.7	373
Weight (lbs/kgs)	192.0	87.0
Terminal*	M8	
Cell(s)	16S/26P	
Case Material	Steel	
Electrolyte	LiFePO4	

^{*}TERMINALTORQUE: 9 Nm +/- 3 / 6.64ft-lb

ELECTRICAL SPECIFICATIONS

Open Circuit Voltage (V)	51.2	
Nominal Energy (kWh)	7.39	
Useable DoD	90%	
Rated Ah Capacity (1C)	129	
Charge Voltage (Vdc)	54.4	
Max Voltage (Vdc)	58.4	
Min Voltage (Vdc)	44.8	
Max Continuous Charge Current (Adc)	130	
Max Continuous Discharge Current (Adc)	130	
Max. Peak Current (Adc)	300	
Self Discharge (25°C / 77°F)	< 3% per month (Battery Off)	
Charge Temperature	Min: 0°C (32°F) Max: 45°C (113°F)	
Discharge Temperature	Min: -20°C (-4°F) Max: 50°C (122°F)	
Storage Temperature	Min: -20°C (-4°F) Max: 45°C (113°F)	

Electrical Specifications at 25°C.

CAUTION: Extra considerations must be given to depths of discharge, operating voltages and currents when designing systems for use at maximum operating

FEATURES

LYNK PORT

- Connects battery string to LYNK Gateway
- Multi-battery BMS communication

HIGH-CURRENT BMS

- Field serviceable BMS and fuse protection
- Plug and Play system wide BMS communication
- Sets Voltage, broadcasts SoC and temperature AES DASHBOARD
- Battery diagnostic software for PC
- · Data export kWh, fault logs to PC
- Update battery BMS firmware
- ACCESSORIES

LYNK SOLAR GATEWAY

- Integrated closed-loop communications with the world's best inverter chargers
- · Plug and play charger configuration

BENEFITS

ENHANCED RUNTIME

- Double the high-current runtime of lead-acid battery
- Up to 100% usable capacity
- Up to 100% depth of discharge

EXTENDED SERVICE LIFE

- 10x the life of lead-acid battery (BCI-06)
- Unlimited Partial State of Charge cycles
- 10-year energy throughput warranty

FAST CHARGING

- Up to 5x faster than new lead-acid batteries
- Up to 10x faster than aged lead-acid batteries
- 2X faster charging than C/2 Rated lithium batteries
- 1C continuous charge rate, regardless of SoC

SURGE POWER

- Power for off-grid inverter surge demands
- Up to 3C peak power discharge rate
- 1C continuous discharge rate

HIGH-EFFICIENCY

- Up to 50% more energy efficient than a lead-acid batterv
- Up to 98% round-trip efficiency

DYNAMIC PERFORMANCE

- · Real-time optimization of the charge rate
- Faster recharge from 0% to 100% SoC than lead-acid batterv

PARALLEL POWER

- Easy to parallel more capacity
- Linear scaling of charge, discharge and peak capacity
- Parallel up to 20 batteries or 160 kWh per LYNK device QUICK INSTALL
- · Fast installation. No special tools
- Drop-in lead-acid replacement

RELIABLE AND SAFE

- LiFePO₄ is thermally safe
- Maintenance-free
- · Steel case and cover
- IP 55 rated

CERTIFIED QUALITY

Discover® manufacturing facilities are fully certified to ISO 9001/14001 and OSHA 18001 standards.

CERTIFICATION STANDARDS

- IEC 62133 • UL 1973
- UL 9540
- UL 2271
- CE
- UN 38.3

SHIPPING CLASSIFICATION

• UN 3480, Class 9 (Lithium batteries)


Minutes of Discharge		
@25A	@100A	
312	78	

^{*} Do not exceed maximum voltage at the battery terminals

Voltage Regulated IU Curve

Balk Absorption | Battery Voltage [V] | 12V 24V 36V 48V | 14.4 | 28.8 | 43.2 | 57.6 | 18.0 | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60% | 60%


Voltage Regulated IU Charging Curve Parameters



Voltage in Relation to Rate of Discharge



Discharge Voltage and Capacity vs. Temperature



NOTES

CAUTION: Direct connection to DC motors without proper safety protection, motor controllers, and external motor voltage clamping systems (such as high power anti-parallel diodes or braking resistor systems) may result in damage to the internal pack protection system which may result in unsafe situations. Please consult Discover technical support before directly connecting any motorloads.

Discover® reserves the right to make adjustments to this publication at any time, without notice or obligation. Data in this publication are for reference use only and models may vary from shown. It is the responsibility of the reader of this information to verify any and all information presented herein. For more information contact us at info@discoverbattery.com

VOLTAGE REGULATED IU CHARGING CURVE

PARAMETERS

Nominal Voltage	
Bulk Current (I1)	65 A recommen
Absorption Voltage (U1)	
Termination Charge Current	12